

**CONTROLLING THE EXTINCTION RATIO**  
**OF OPTICAL TRANSMITTERS**

*by Inventors*

Christopher Martinez and Qingsheng Tan

**CROSS REFERENCE TO RELATED APPLICATIONS**

This application claims priority from Martinez et al.'s provisional application U.S. Serial No. 60/279,777, filed on March 30, 2001, entitled "METHOD AND APPARATUS FOR CONTROLLING THE EXTINCTION RATIO OF OPTICAL TRANSMITTERS," incorporated herein by reference.

**BACKGROUND OF THE INVENTION**

There are various kinds of optical transmitters. One method of producing an optical transmitter is to directly modulate a laser diode using a laser driver. Laser drivers provide a means to switch currents in and out of laser diodes. These currents are typically driven at high data rates and are set and controlled by the laser driver for optimum performance of laser operation.

As will be appreciated by those skilled in the art, the characteristics of a laser diode change over time and with temperature. Well designed laser drivers attempt to compensate for these changes through adjustments in diode currents. To avoid laser turn-on and turn-off delays in light emission for high speed operation, a bias current, which is typically higher than the threshold current of the laser diode, is generally supplied to the laser diode. As is known in this field, when the bias current significantly exceeds the threshold value, the extinction ratio of the optical

emission rapidly deteriorates, resulting in a receiver sensitivity penalty for signal transmission.

The extinction ratio of an optical signal is a ratio of the amount of optical power that is transmitted during a "1/on" period to the amount of optical power that is transmitted during a "0/off" period. In other words, the extinction ratio is the ratio of the optical-energy level of a binary "1" to that of a binary "0" level of a modulated signal. If the laser characteristics change over time and temperature with no compensation provided by the laser driver, the extinction ratio will decrease and the optical system performance will degrade, showing increased error rates. In most circumstances, a desirable extinction ratio is generally about 8.2 dB or better.

A standard laser driver has an Imod current, which is switched in and out of the laser diode providing a means to transmit a "1/on" or "0/off" signal. The optical output of the laser is therefore P1 when on, and P0 when off. The current which supplies power to the laser driver is called the modulation current Imod, and bias current Ibias.

The Ibias value sets the base line current for the laser when it is off, which is therefore the P0. The Imod current is turned on through a data input, electrically coupled to a first and second transistors and provides enough current to turn the laser on, the P1 setting. An extinction ratio is simply the ratio of P1 over P0.

PRIOR ART FIG. 1 depicts a typical laser driver 10. The laser driver 10 includes a photocurrent source, Iphoto 4, and a current source 5. A laser 1 emits light 2 to a photo current monitor 3. The photo current, Iphoto 4, is set by a user. The Imod current source 5 is controlled by the input of data through an input switch 6, which is sent through transistors 7 in a well known fashion. A block 9 is used to set an Ibias current 8. The total modulation current is simply the Imod current.

FIG. 2 graphically shows how either time or temperature decreases the extinction ratio of a laser diode of the prior art. The characteristics of laser diode optical output (vertical axis) versus laser current (horizontal axis) for an optimally functioning laser **20** has better performance and a steeper slope than a laser which is below optimal level **21** due to problems such as hysteresis or changes in the operating temperature. The optical output power at 1 versus 0 is represented by **P1** and **P0** for the optimal laser and **P1'** and **P0'** for the less functional laser. Both states of the laser have the same average optical output due to the feedback caused by the Ibias circuitry (see elements **9** and **10** of FIG. 1). The actual levels of power at 1, **P1** and **P1'** respectively, differ because of this feedback loop. So as a result the extinction ratio, which is power at 1 over power at 0 ( $P1/P0$ ), gets smaller as the laser loses efficiency.

Typically, laser drivers do not compensate for the extinction ratio. Laser drivers that do are complex and require expensive peak detectors.

Some attempts to compensate for the extinction ratio can be found, for example, in U.S. patent 6,014,235. In that patent there is taught an optical-loop buffer that mitigates the reduction in the buffered signal's extinction ratio and substantially restores (e.g., maintains or increases) the buffered signal's extinction ratio to its original value, thereby extending the number of circulations, and hence the storage time, for which the buffered signal can remain in the buffer without the extinction ratio falling below an acceptable minimum. The optical buffer restores the extinction ratio of the buffered signal and thereby extends the length of time for which the signal can be stored. However this approach uses a complex assembly of optical components and as a result, can not be easily implemented into an existing circuit due its size and complexity.

Accordingly, what is needed is a simpler way to compensate for the deterioration of the extinction ratio and not add to circuit complexity.

## SUMMARY OF THE INVENTION

It is a purpose of the present invention to provide a simplified scheme to control the extinction ratio of laser transmitters.

5 A standard laser driver controls laser operation through the use of an Imod current, which is switched in and out of the laser diode providing a means to transmit a "1/on" or "0/off". The Imod current can be controlled and set externally. An Ibias current is then used to control the average current in the laser and compensates for increases in a laser's threshold current by having its current increased, while the Imod current itself does not change. However, when this is done, the extinction ratio is reduced since there is no compensation for decreases in laser's slope efficiency. The present invention compensates for decreases in the extinction ratio by feeding forward a portion of the Ibias current to the Imod current source. The percentage of the portion being fed forward can be controlled externally by a user to compensate for changes in the laser. Therefore the Imod total becomes a function of the set Imod current and some portion of the Ibias current. This controls the extinction ratio by making the optical output power in the "1/on" state, when the laser is at a higher temperature, almost the same as that as when it is functioning normally. The extinction ratio can therefore be stabilized  
10  
15  
20 by using embodiments of this invention.

Preferably the portion of the Ibias current being fed forward to the Imod current is between 30-200 %.

One advantage of the present invention is that it prevents deterioration of the extinction ratio. Another advantage is that the maintenance of the extinction ratio is  
25 accomplished with a minimal modification of an existing circuit and therefore is economical.

These and other advantages of the present invention will become apparent to those skilled in the art upon a reading of the following descriptions and a study of the various FIGS. of the drawing.

11  
12  
13  
14  
15  
16  
17  
18  
19  
20  
21  
22  
23  
24  
25  
26  
27  
28  
29  
30  
31  
32  
33  
34  
35  
36  
37  
38  
39  
40  
41  
42  
43  
44  
45  
46  
47  
48  
49  
50  
51  
52  
53  
54  
55  
56  
57  
58  
59  
60  
61  
62  
63  
64  
65  
66  
67  
68  
69  
70  
71  
72  
73  
74  
75  
76  
77  
78  
79  
80  
81  
82  
83  
84  
85  
86  
87  
88  
89  
90  
91  
92  
93  
94  
95  
96  
97  
98  
99  
100  
101  
102  
103  
104  
105  
106  
107  
108  
109  
110  
111  
112  
113  
114  
115  
116  
117  
118  
119  
120  
121  
122  
123  
124  
125  
126  
127  
128  
129  
130  
131  
132  
133  
134  
135  
136  
137  
138  
139  
140  
141  
142  
143  
144  
145  
146  
147  
148  
149  
150  
151  
152  
153  
154  
155  
156  
157  
158  
159  
160  
161  
162  
163  
164  
165  
166  
167  
168  
169  
170  
171  
172  
173  
174  
175  
176  
177  
178  
179  
180  
181  
182  
183  
184  
185  
186  
187  
188  
189  
190  
191  
192  
193  
194  
195  
196  
197  
198  
199  
200  
201  
202  
203  
204  
205  
206  
207  
208  
209  
210  
211  
212  
213  
214  
215  
216  
217  
218  
219  
220  
221  
222  
223  
224  
225  
226  
227  
228  
229  
230  
231  
232  
233  
234  
235  
236  
237  
238  
239  
240  
241  
242  
243  
244  
245  
246  
247  
248  
249  
250  
251  
252  
253  
254  
255  
256  
257  
258  
259  
260  
261  
262  
263  
264  
265  
266  
267  
268  
269  
270  
271  
272  
273  
274  
275  
276  
277  
278  
279  
280  
281  
282  
283  
284  
285  
286  
287  
288  
289  
290  
291  
292  
293  
294  
295  
296  
297  
298  
299  
300  
301  
302  
303  
304  
305  
306  
307  
308  
309  
310  
311  
312  
313  
314  
315  
316  
317  
318  
319  
320  
321  
322  
323  
324  
325  
326  
327  
328  
329  
330  
331  
332  
333  
334  
335  
336  
337  
338  
339  
340  
341  
342  
343  
344  
345  
346  
347  
348  
349  
350  
351  
352  
353  
354  
355  
356  
357  
358  
359  
360  
361  
362  
363  
364  
365  
366  
367  
368  
369  
370  
371  
372  
373  
374  
375  
376  
377  
378  
379  
380  
381  
382  
383  
384  
385  
386  
387  
388  
389  
390  
391  
392  
393  
394  
395  
396  
397  
398  
399  
400  
401  
402  
403  
404  
405  
406  
407  
408  
409  
410  
411  
412  
413  
414  
415  
416  
417  
418  
419  
420  
421  
422  
423  
424  
425  
426  
427  
428  
429  
430  
431  
432  
433  
434  
435  
436  
437  
438  
439  
440  
441  
442  
443  
444  
445  
446  
447  
448  
449  
450  
451  
452  
453  
454  
455  
456  
457  
458  
459  
460  
461  
462  
463  
464  
465  
466  
467  
468  
469  
470  
471  
472  
473  
474  
475  
476  
477  
478  
479  
480  
481  
482  
483  
484  
485  
486  
487  
488  
489  
490  
491  
492  
493  
494  
495  
496  
497  
498  
499  
500  
501  
502  
503  
504  
505  
506  
507  
508  
509  
510  
511  
512  
513  
514  
515  
516  
517  
518  
519  
520  
521  
522  
523  
524  
525  
526  
527  
528  
529  
530  
531  
532  
533  
534  
535  
536  
537  
538  
539  
540  
541  
542  
543  
544  
545  
546  
547  
548  
549  
550  
551  
552  
553  
554  
555  
556  
557  
558  
559  
560  
561  
562  
563  
564  
565  
566  
567  
568  
569  
570  
571  
572  
573  
574  
575  
576  
577  
578  
579  
580  
581  
582  
583  
584  
585  
586  
587  
588  
589  
590  
591  
592  
593  
594  
595  
596  
597  
598  
599  
600  
601  
602  
603  
604  
605  
606  
607  
608  
609  
610  
611  
612  
613  
614  
615  
616  
617  
618  
619  
620  
621  
622  
623  
624  
625  
626  
627  
628  
629  
630  
631  
632  
633  
634  
635  
636  
637  
638  
639  
640  
641  
642  
643  
644  
645  
646  
647  
648  
649  
650  
651  
652  
653  
654  
655  
656  
657  
658  
659  
660  
661  
662  
663  
664  
665  
666  
667  
668  
669  
670  
671  
672  
673  
674  
675  
676  
677  
678  
679  
680  
681  
682  
683  
684  
685  
686  
687  
688  
689  
690  
691  
692  
693  
694  
695  
696  
697  
698  
699  
700  
701  
702  
703  
704  
705  
706  
707  
708  
709  
710  
711  
712  
713  
714  
715  
716  
717  
718  
719  
720  
721  
722  
723  
724  
725  
726  
727  
728  
729  
730  
731  
732  
733  
734  
735  
736  
737  
738  
739  
740  
741  
742  
743  
744  
745  
746  
747  
748  
749  
750  
751  
752  
753  
754  
755  
756  
757  
758  
759  
760  
761  
762  
763  
764  
765  
766  
767  
768  
769  
770  
771  
772  
773  
774  
775  
776  
777  
778  
779  
780  
781  
782  
783  
784  
785  
786  
787  
788  
789  
790  
791  
792  
793  
794  
795  
796  
797  
798  
799  
800  
801  
802  
803  
804  
805  
806  
807  
808  
809  
810  
811  
812  
813  
814  
815  
816  
817  
818  
819  
820  
821  
822  
823  
824  
825  
826  
827  
828  
829  
830  
831  
832  
833  
834  
835  
836  
837  
838  
839  
840  
841  
842  
843  
844  
845  
846  
847  
848  
849  
850  
851  
852  
853  
854  
855  
856  
857  
858  
859  
860  
861  
862  
863  
864  
865  
866  
867  
868  
869  
870  
871  
872  
873  
874  
875  
876  
877  
878  
879  
880  
881  
882  
883  
884  
885  
886  
887  
888  
889  
890  
891  
892  
893  
894  
895  
896  
897  
898  
899  
900  
901  
902  
903  
904  
905  
906  
907  
908  
909  
910  
911  
912  
913  
914  
915  
916  
917  
918  
919  
920  
921  
922  
923  
924  
925  
926  
927  
928  
929  
930  
931  
932  
933  
934  
935  
936  
937  
938  
939  
940  
941  
942  
943  
944  
945  
946  
947  
948  
949  
950  
951  
952  
953  
954  
955  
956  
957  
958  
959  
960  
961  
962  
963  
964  
965  
966  
967  
968  
969  
970  
971  
972  
973  
974  
975  
976  
977  
978  
979  
980  
981  
982  
983  
984  
985  
986  
987  
988  
989  
990  
991  
992  
993  
994  
995  
996  
997  
998  
999  
1000

## **BRIEF DESCRIPTION OF THE DRAWINGS**

FIG. 1 is a diagram of a laser diode of the prior art.

FIG. 2 is a chart of a laser diode curve according to the prior art.

FIG. 3 shows one embodiment of the invention as feeding forward a portion of the Ibias current to the Imod current.

FIG. 4 shows a diagram of how the present invention improves performance over the prior art.

FIG. 5 is a diagram that shows the behavior of the extinction ratio versus temperature with and without modulation compensation used in the present invention.

## DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENT(S)

FIGS. 1 and 2 were previously described in relation to the prior art.

FIG. 3 shows one embodiment of how the present invention helps to keep  
5 the extinction ratio constant. A portion of the Ibias current **30** set by a user is fed forward into the current controlling the laser **31**. Therefore, the Imod total becomes the set Imod plus a percentage of the Ibias. The percentage of the Ibias current fed forward to the I-mod current source K, can be set by the user **30** and can be any percentage, but is preferably between 30 and 200 percent of the Ibias current. The embodiment in FIG. 3 shows the  $(K \cdot I_{bias})$  current value fed forward to a second current source **31** electrically coupled in parallel to the first I-mod current source **5**; essentially a branch in the second current source **31** is a branch arm **32**. In this embodiment the  $(K \cdot I_{bias})$  current **30** is fed forward into the second current source **31**, but it can also be fed forward into the first Imod current source, or in other manner which will be equally apparent to one of ordinary skill in the art.

The Imod current may be almost any conceivable current value set by the user, restricted only by the operating parameters of the first and second transistor **7** and the diode laser. Most laser systems, though, would operate within a range of  
20 between 2 and 100 milliamps, though a particularly preferred embodiment is approximately 40 milliamps. At this level, the Ibias current value fed forward by the present invention would preferably be set at approximately 10 milliamps. The preferred range of the  $(K \cdot I_{bias})$  current value would therefore be from 3 to 20 milliamps.

25 FIG. 4, graphically shows how the extinction ratio is kept more constant by this invention. The characteristics of laser diode optical output (vertical axis) versus laser current (horizontal axis) for a laser, which is below optimal level **23**

due to problems such as aging or the changing of the operating temperature, now has a performance and slope more equal to that of an optimally functioning laser 20. The extinction ratio, which is power at 1 over power at 0 ( $P_1/P_0$ ), is now kept a more constant level over time and temperature.

5 FIG. 5 is a diagram that shows the behavior of the extinction ratio versus temperature with and without the modulation compensation used in the present invention. As can be seen, if modulation compensation of the present invention is not used, the extinction ratio decays with increasing temperature (curve 100). When modulation compensation is applied (curve 102), the extinction ratio advantageously remains more or less constant with increasing temperature.

10 In view of the foregoing, it will be appreciated that the present invention prevents deterioration of the extinction ratio. Additionally, the maintenance of the extinction ratio is accomplished with a minimal modification of an existing circuit and therefore the implementation is economical.

15 While various embodiments have been described above, it should be understood that they have been presented by way of example only, and not limitation. Thus, the breadth and scope of a preferred embodiment should not be limited by any of the above described exemplary embodiments, but in accordance with the true spirit and scope of the invention.

20 Other embodiments are within the following claims.

*What is claimed is:*